

Molded Case Circuit Breakers

# ED-Frame Sentron Series Circuit Breaker

1, 2, & 3-pole; 15 to 125 Amperes



### Ratings & Markings (UL 489 AIR Interrupting Ratings)

Breaker Type	RMS Symmetrical Amperes (kA)									
	Volts AC (50/60Hz)						Volts DC			
	120	240	277	347	480	600	125	250	500	600
ED2 (1-P)	10	–	–	–	–	–	5	–	–	–
ED2 (2, 3-P)	–	10	–	–	–	–	–	5 (2-P)	–	–
ED4 (1-P)	65	–	22	–	–	–	30	–	–	–
ED4 (2, 3-P)	–	65	–	–	18	–	–	30 (2-P)	–	–
ED6 (1-P)	–	–	–	30	–	–	–	30	–	–
ED6 (2, 3-P)	–	65	–	–	25	18	–	–	18 (3-P)	–
ED6 (3-P)	–	–	–	–	–	–	–	–	–	10
HED4 (1-P) (15-30A)	100	–	65	–	–	–	30	–	–	–
HED4 (1-P) (35-100A)	100	–	25	–	–	–	30	–	–	–
HED4 (2, 3P)	–	100	–	–	42	–	–	30 (2-P)	–	–
HHED6 (2, 3-P)	–	100	–	–	65	18	–	–	–	–
CED6 (2, 3-P)	–	200	–	–	200	100	–	50 (2-P)	30 (3-P)	–

Footnote: 600VDC for ED6 only

### Dimensions

Breaker Type	Poles	Length	Width	Depth	D-1 (over handle)
ED2, ED4, ED6, HED4	1	6.35	1	3.92	4.56
	2	6.35	2	3.92	4.56
	3	6.35	3	3.92	4.56
HHED6	2	6.53	2	3.92	4.56
	3	6.53	3	3.92	4.56
CED6	2	9.58	2	3.92	4.56
	3	9.58	3	3.92	4.56



## Magnetic Trip Only – ETI Motor Circuit Protector

Breaker Type	Ampere Rating	Instantaneous Trip Range <sup>①</sup>		Complete Circuit Breaker Without Lugs <sup>③</sup>	
		Minimum <sup>②</sup>	Maximum <sup>②</sup>	Catalog Number 2-Pole	Catalog Number 3-Pole
ED6-A 600V AC 250V DC	1	2.6	9	—	ED63A001
	2	7	22	—	ED63A002
	3	10	35	—	ED63A003
	5	16	54	—	ED63A005
	10	30	100	—	ED63A010
	25	55	180	—	ED63A025
	30	80	270	—	ED63A030
	40	115	375	—	ED63A040
	50	180	600	—	ED63A050
	100	315	1000	—	ED63A100
CED6-A 600V AC 250V DC	125	500	1250	—	ED63A125
	1	2.6	9	—	CED63A001
	2	7	22	—	CED63A002
	3	10	35	—	CED63A003
	5	16	54	—	CED63A005
	10	30	100	—	CED63A010
	25	55	180	—	CED63A025
	30	80	270	—	CED63A030
	40	115	375	—	CED63A040
	50	180	600	—	CED63A050
100	315	1000	—	CED63A100	
125	500	1250	—	CED63A125	

## Shunt Trip Combinations

Control Voltage		1 Shunt Trip	1 Shunt Trip and 1 Auxiliary Switch	1 Shunt Trip 1 Auxiliary Switch and 1 Alarm Switch	1 Shunt Trip and 1 Alarm Switch	1 Shunt Trip and 2 Auxiliary Switches
AC	DC	Catalog Number	Catalog Number	Catalog Number	Catalog Number	Catalog Number
24	—	S17ED60	—	—	—	—
48	—	S18ED60	—	—	—	—
120	—	S01ED60	S01ED62A	S01ED62AB	S01ED62B	S01ED62AA
208	—	—	S02ED62A	S02ED62AB	S02ED62B	S02ED62AA
240	—	S03ED60	S03ED62A	S03ED62AB	S03ED62B	S03ED62AA
277	—	S15ED60	S15ED64A	S15ED64AB	S15ED64B	—
480	—	S04ED60	S04ED64A	S04ED64AB	S04ED64B	—
—	12	S16ED60	S16ED62A	—	—	—
—	24	S07ED60	S07ED62A	S07ED62AB	S07ED62B	S07ED62AA
—	48	S09ED60	S09ED62A	S09ED62AB	S09ED62B	S09ED62AA
—	125	S11ED60	S11ED62A	S11ED62AB	S11ED62B	S11ED62AA
—	250	S13ED60	S13ED62A	S13ED62AB	S13ED62B	S13ED62AA

## Undervoltage Trip Combinations

Control Voltage		1 Undervoltage Trip	1 Undervoltage Trip and 1 Auxiliary Switch	1 Undervoltage Trip and 1 Auxiliary Switch and 1 Alarm Switch	1 Undervoltage Trip and 1 Alarm Switch	1 Undervoltage Trip and 2 Auxiliary Switches
AC	DC	Catalog Number	Catalog Number	Catalog Number	Catalog Number	Catalog Number
120	—	U01ED60	U01ED62A	U01ED62AB	U01ED62B	U01ED62AA
208	—	U02ED60	U02ED62A	U02ED62AB	U02ED62B	U02ED62AA
240	—	U03ED60	U03ED62A	U03ED62AB	U03ED62B	U03ED62AA
277	—	U16ED60	U16ED64A	U16ED64AB	U16ED64B	—
480	—	U06ED60	U06ED64A	U06ED64AB	U06ED64B	—
600	—	U08ED60	—	—	—	—
—	24	U13ED60	U13ED62A	U13ED62AB	U13ED62B	U13ED62AA
—	48	U14ED60	U14ED62A	U14ED62AB	U14ED62B	U14ED62AA
—	125	U10ED60	U10ED62A	U10ED62AB	U10ED62B	U10ED62AA
—	250	U12ED60	U12ED62A	—	—	U12ED62AA

① When applied on DC Circuits — Trip levels will increase approximately +15 to 20%.

② Tolerance -20%/+30% for lowest setting. All other settings are -20%/+20%

③ Connectors included when ordering by circuit breaker catalog number for HEM, ED and CED6 ETIs. Order ETI circuit breaker and lugs (2 per pole) separately for the FXD6, CFD6, MXD6, CMD6, JXD6, CJD6, LXD6 and CLD6 ETI's.

## Auxiliary Switch Combinations

Maximum Voltage		1 Auxiliary Switch	1 Alarm Switch and 1 Auxiliary Switch	2 Auxiliary Switches	1 Alarm Switch and 2 Auxiliary Switches
AC	DC	Catalog Number	Catalog Number	Catalog Number	Catalog Number
240	250	A01ED62	A01ED62B	A02ED62	A02ED62B
480	–	A01ED64	A01ED64B	–	–

Maximum Voltage		1 Auxiliary Switch	
AC	DC	Catalog Number	
–	24	A01EDLV	Gold Plated Contacts — for PLC use

## Alarm Switch Only

Maximum Voltage		1 Alarm Switch
AC	DC	Catalog Number
240	250	B00ED62
480	–	B00ED64

## Ground Fault Sensing Relay Kit — Equipment Protection Only

FOr Use With Breaker Frame	Number of Poles	Description	Catalog Number	
			30mA	5mA
CED6, ED2, ED4, ED6, EFC, EFF, HED4, HHED6	1, 2, 3	Basic Kit	GF01ED60	GF01ED65
		Basic Kit with Normally Open Bell Alarm	GF01ED60B0	GF01ED65B0
		Basic Kit with Normally Closed Bell Alarm	GF01ED60BC	GF01ED65BC

### Published by Siemens 2020

Siemens Industry, Inc.  
3617 Parkway Ln.  
Peachtree Corners, GA 30092

Siemens Technical Support: 1-800-333-7421  
info.us@siemens.com

Printed in USA-CP  
Order No. CPDS-ED123-0520  
All Rights Reserved  
© 2020, Siemens Industry, Inc.  
usa.siemens.com/Sentron

The technical data presented in this document is based on an actual case or on as-designed parameters, and therefore should not be relied upon for any specific application and does not constitute a performance guarantee for any projects. Actual results are dependent on variable conditions. Accordingly, Siemens does not make representations, warranties, or assurances as to the accuracy, currency or completeness of the content contained herein. If requested, we will provide specific technical data or specifications with respect to any customer's particular applications. Our company is constantly involved in engineering and development. For that reason, we reserve the right to modify, at any time, the technology and product specifications contained herein.