

# Eaton 197503

Catalog Number: 197503

Eaton DA1 Frequency inverter, 500 V AC, 3-phase, 65 A, 45 kW, IP20/NEMA 0, Additional PCB protection, DC link choke, FS5



## General specifications

|                                    |                       |
|------------------------------------|-----------------------|
| <b>Product Name</b>                | <b>Catalog Number</b> |
| Eaton DA1 Variable frequency drive | 197503                |

|                   |               |
|-------------------|---------------|
| <b>Model Code</b> | <b>EAN</b>    |
| DA1-35065NB-B20C  | 4015081940783 |

|                             |                       |
|-----------------------------|-----------------------|
| <b>Product Length/Depth</b> | <b>Product Height</b> |
| 261 mm                      | 485 mm                |

|                      |                       |
|----------------------|-----------------------|
| <b>Product Width</b> | <b>Product Weight</b> |
| 234 mm               | 18.2 kg               |

|   |  |
|---|--|
| <b>Certifications</b>                   | <b>Catalog Notes</b>   |
| EAC                                     | The brake resistors are assigned based on the maximum rated power of the variable frequency drive. Additional brake resistors and designs (e.g. different duty cycles) are available upon request. |
| IEC/EN 61800-3                          |  |
| RCM                                     |  |
| UL File No.: E172143                    |  |
| UL report applies to both US and Canada |  |
| IEC/EN 61800-2                          |  |
| UL 508C                                 |  |
| CE                                      |  |
| CUL                                     |  |
| RoHS, ISO 9001                          |  |
| UL                                      |  |
| IEC/EN61800-3                           |  |
| IEC/EN61800-5                           |  |



UkrSEPRO  
 UL Category Control No.: NMMS, NMMS7  
 Safety: EN 61800-5-1: 2003  
 Certified by UL for use in Canada

## General

### Cable length

100 m, screened, maximum permissible cable length  
150 m, unscreened, maximum permissible cable length  
200 m, unscreened, with motor choke, maximum permissible cable length  
200 m, screened, with motor choke, maximum permissible cable length

### Communication interface

PROFINET, optional  
DeviceNet, optional  
PROFIBUS, optional  
Modbus RTU  
CANopen®  
Modbus-TCP, optional  
EtherCAT, optional  
OP-Bus (RS485)  
Ethernet IP, optional  
SmartWire-DT, optional

### Connection to SmartWire-DT

In conjunction with DX-NET-SWD1 SmartWire DT module  
Yes

### Degree of protection

IP20  
NEMA Other

### Fitted with:

OLED display  
DC link choke  
Internal DC link  
Breaking resistance  
Control unit  
IGBT inverter  
Brake chopper  
PC connection  
Additional PCB protection

### Frame size

FS5

### Functions

4-quadrant operation possible

### Mounting position

Vertical

### Product Category

## Climatic environmental conditions

### Ambient operating temperature - min

-10 °C

### Altitude

Max. 4000 m  
Max. 1000 m  
Above 1000 m with 1 % derating per 100 m

### Ambient operating temperature - max

50 °C

### Ambient operating temperature at 150% overload - min

-10 °C

### Ambient operating temperature at 150% overload - max

50 °C

### Ambient storage temperature - min

-40 °C

### Ambient storage temperature - max

60 °C

### Climatic proofing

< 95 average relative humidity (RH), no condensation, no corrosion

## Main circuit

### Efficiency

97.9 % ( $\eta$ )

### Heat dissipation at current/speed

1090 W at 100% current and 90% speed  
280 W at 25% current and 0% speed  
350 W at 25% current and 50% speed  
390 W at 50% current and 0% speed  
490 W at 50% current and 50% speed  
550 W at 50% current and 90% speed  
740 W at 100% current and 0% speed  
900 W at 100% current and 50% speed

### Input current ILN at 150% overload

75.8 A

### Leakage current at ground IPE - max

65 mA

### Mains switch-on frequency

Variable frequency drives

Maximum of one time every 30 seconds

#### Protection

Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4)

#### Mains voltage - min

500 V

#### Protocol

EtherNet/IP

CAN

TCP/IP

MODBUS

DeviceNet

PROFIBUS

PROFINET IO

Other bus systems

#### Mains voltage - max

600 V

#### Operating mode

Speed control with slip compensation

U/f control

Optional: Vector control with feedback (CLV)

Sensorless vector control (SLV)

#### Safety function/level

STO (Safe Torque Off, SIL2, PLc Cat 2)

#### Output frequency - min

0 Hz

#### Suitable for

Branch circuits, (UL/CSA)

#### Output frequency - max

500 Hz

#### Output voltage (U<sub>2</sub>)

600 V AC, 3-phase

500 V AC, 3-phase

#### Overload current I<sub>L</sub> at 150% overload

97.5 A

#### Rated control supply voltage

10 V DC (U<sub>s</sub>, max. 10 mA)

#### Rated frequency - min

48 Hz

#### Rated frequency - max

62 Hz

#### Rated operational current (I<sub>e</sub>) at 150% overload

65 A

#### Rated operational power at 500 V, 50 Hz, 3-phase

45 kW

#### Rated operational power at 525 V, 50 Hz, 3-phase

45 kW

#### Rated operational voltage

500 V AC, 3-phase

600 V AC, 3-phase

#### Resolution

0.1 Hz (Frequency resolution, setpoint value)

#### Short-circuit protection

NH fuse used together with TB00-D fuse base, Power wiring, Assigned switching and protective elements

LPJ fuse used together with JM60100-3 fuse base, Power wiring, Assigned switching and protective elements

#### Short-circuit protection rating

100 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring

#### Starting current - max

200 %, IH, max. starting current (High Overload), for 4 seconds every 40 seconds, Power section

#### Supply frequency

50/60 Hz

#### Switching frequency

8 kHz, 4 - 24 kHz adjustable (audible), fPWM, Power section, Main circuit

#### System configuration type

AC supply systems with earthed center point

#### Voltage rating - max

600 VAC

## Motor rating

Assigned motor current IM at 500 V, 50 Hz, 150% overload  
65 A

Assigned motor current IM at 525 V, 50 Hz, 150% overload  
62 A

Assigned motor current IM at 550 - 600 V, 60 Hz, 150% overload  
62 A

Assigned motor power at 575/600 V, 60 Hz, 3-phase  
60 HP

## Apparent power

Apparent power at 600 V  
67.55 kVA

## Braking function

#### Braking resistance

12 Ω

#### Braking torque

Max. 30 % MN, Standard - Main circuit

Max. 100 % of rated operational current Ie with external braking resistor - Main circuit

Adjustable to 100 % (DC)

#### Switch-on threshold for the braking transistor

975 VDC

## Control circuit

#### Number of inputs (analog)

2

#### Number of inputs (digital)

5

#### Number of outputs (analog)

2

#### Number of outputs (digital)

2

#### Number of relay outputs

## Design verification

#### 10.2.2 Corrosion resistance

Meets the product standard's requirements.

#### 10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

#### 10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

#### 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

2 (parameterizable, 1 N/O and 1 changeover contact, 6 A (250 V, AC-1) / 5 A (30 V, DC-1))

**Rated control voltage (Uc)**

24 V DC (external, max. 100 mA)

**10.2.4 Resistance to ultra-violet (UV) radiation**

Meets the product standard's requirements.

**10.2.5 Lifting**

Does not apply, since the entire switchgear needs to be evaluated.

**10.2.6 Mechanical impact**

Does not apply, since the entire switchgear needs to be evaluated.

**10.2.7 Inscriptions**

Meets the product standard's requirements.

**10.3 Degree of protection of assemblies**

Does not apply, since the entire switchgear needs to be evaluated.

**10.4 Clearances and creepage distances**

Meets the product standard's requirements.

**10.6 Incorporation of switching devices and components**

Does not apply, since the entire switchgear needs to be evaluated.

**10.7 Internal electrical circuits and connections**

Is the panel builder's responsibility.

**10.8 Connections for external conductors**

Is the panel builder's responsibility.

**10.9.2 Power-frequency electric strength**

Is the panel builder's responsibility.

**10.9.3 Impulse withstand voltage**

Is the panel builder's responsibility.

**10.9.4 Testing of enclosures made of insulating material**

Is the panel builder's responsibility.

**10.10 Temperature rise**

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

**10.11 Short-circuit rating**

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

**10.12 Electromagnetic compatibility**

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

**10.13 Mechanical function**

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## Resources

### Application notes

[PID controller](#)

[Starting, Stopping and Operation](#)

[Use of multiple ramps](#)

[Access to Parameter Level 2 and 3 Parameter Lock RESET](#)

[Closed Loop Vector Control](#)

[Update DX-COM-STICK3](#)

[Connecting drives to generator supplies](#)

[I/O Configuration](#)

[Master slave operation](#)

[Operating Permanent Magnet and Brushless DC Motors](#)

[Motor data Motor Protection V/f curves for induction motors](#)

[Dual Rating What exactly does that mean?](#)

[The OP System Bus - Parameterizing - Control](#)

[Dependency of the output current on switching frequency and ambient temperature](#)

[DX-COM-STICK3\\_Connection](#)

[Conformal Coating](#)

[Vector Control of Induction Motors](#)

[Setpoint Setting](#)

[Electromagnetic compatibility \(EMC\)](#)

[How does the internal motor protection work?](#)

[Hoist applications](#)

[Equal load sharing with the droop function](#)

### Brochures

[eaton-powerxl-variable-frequency-drives-dc1-da1-brochure-br040001en-en-us.pdf](#)

### Catalogs

[Drives - Product range catalog](#)

[Product Range Catalog Drives Engineering](#)

### Declarations of conformity

[DA-DC-00003964.pdf](#)

[DA-DC-00005020.pdf](#)

[DA-DC-00004184.pdf](#)

[DA-DC-00005021.pdf](#)

### Drawings

[eaton-frequency-inverter-dimensions-013.eps](#)

## eCAD model

DA-CE-ETN.DA1-35065NB-B20C

## Installation instructions

[eaton-da1-variable-frequency-drive-il040049zu.pdf](#)

## Installation videos

[PowerXL Variable Frequency Drives DC1 and DA1 - EN](#)

[Video PowerXL DA1](#)

## Manuals and user guides

[MN040018\\_EN](#)

[eaton-da1-variable-frequency-drive-mn040063-en-us.pdf](#)

[MN04020005Z\\_EN](#)

[MN040003\\_EN](#)

[MN04020006Z\\_EN](#)

[eaton-canopen-communication-manual-for-variable-frequency-drives-variable-speed-starters-da1-db1-dc1-de11-mn040019-en-us.pdf](#)

## mCAD model

[DA-CD-da1\\_fs5\\_ip20](#)

[DA-CS-da1\\_fs5\\_ip20](#)

## Multimedia

Looking for variable frequency drives DC1 and DA1 which can be used in harsh environments?

[System solutions based on EtherCAT](#)

## Product notifications

[eaton-drives-ecodesign-directive-mz040046en-en.pdf](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)