

Molded Case Circuit Breakers

FD-Frame Sentron™ Series Circuit Breaker

2 & 3-Pole; 70-250 Amperes



Ratings & Markings (UL 489 AIR Interrupting Ratings)

Breaker Type	RMS Symmetrical Amperes (kA)					Frame Only - Interchangeable Trip		
	Volts AC (50/60Hz)			Volts DC		Breaker Type	Frame (2-Pole)	Frame (3-Pole)
	240	480	600	250	500			
FD6-A, FXD6-A	65	35	22	30 (2-Pole)	18 (3-Pole)	FD6-A	FD62F250	FD63F250
HFD6, HFXD6	100	65	25	30 (2-Pole)	25 (3-Pole)	HFD6	HFD62F250	HFD63F250
HHFD6, HHFXD6	200	100	25	—	—	HHFD6	—	HHFD63F250
CFD6	200	200	100	30 (2-Pole)	50 (3-Pole)	—	—	—

Dimensions

Breaker Type	Length	Width	Depth	D-1 (to handle)
FD6-A, FXD6-A, HFD6, HFXD6 HHFD6, HHFXD6	9.50 in	4.50 in	4.0 in	5.25 in
CFD6	14.25 in	4.50 in	4.0 in	5.25 in

Frames

Trip Amperage	Poles	Non-interchangeable Trip Assembled with no lugs				Interchangeable Trip Not assembled - shipped with CU/AL lugs			Trip Unit Only
		FXD6-A	HFXD6	HHFXD6	CFD6	FD6-A	HFD6	HHFD6	
70	2	FXD62B070	—	—	—	FD62B070	HFD62B070	—	FD62T070
80	2	FXD62B080	—	—	—	FD62B080	HFD62B080	—	FD62T080
90	2	FXD62B090	—	—	—	FD62B090	HFD62B090	—	FD62T090
100	2	FXD62B100	—	—	—	FD62B100	HFD62B100	—	FD62T100
110	2	FXD62B110	—	—	—	FD62B110	HFD62B110	—	FD62T110
125	2	FXD62B125	—	—	—	FD62B125	HFD62B125	—	FD62T125
150	2	FXD62B150	—	—	—	FD62B150	HFD62B150	—	FD62T150
175	2	FXD62B175	—	—	—	FD62B175	HFD62B175	—	FD62T175
200	2	FXD62B200	—	—	—	FD62B200	HFD62B200	—	FD62T200
225	2	FXD62B225	—	—	—	FD62B225	HFD62B225	—	FD62T225
250	2	FXD62B250	—	—	—	FD62B250	HFD62B250	—	FD62T250
70	3	FXD63B070	HFXD63B070	HHFXD63B070	CFD63B070	FD63B070	HFD63B070	HHFD63B070	FD63T070
80	3	FXD63B080	HFXD63B080	HHFXD63B080	CFD63B080	FD63B080	HFD63B080	HHFD63B080	FD63T080
90	3	FXD63B090	HFXD63B090	HHFXD63B090	CFD63B090	FD63B090	HFD63B090	HHFD63B090	FD63T090
100	3	FXD63B100	HFXD63B100	HHFXD63B100	CFD63B100	FD63B100	HFD63B100	HHFD63B100	FD63T100
110	3	FXD63B110	HFXD63B110	HHFXD63B110	CFD63B110	FD63B110	HFD63B110	HHFD63B110	FD63T110
125	3	FXD63B125	HFXD63B125	HHFXD63B125	CFD63B125	FD63B125	HFD63B125	HHFD63B125	FD63T125
150	3	FXD63B150	HFXD63B150	HHFXD63B150	CFD63B150	FD63B150	HFD63B150	HHFD63B150	FD63T150
175	3	FXD63B175	HFXD63B175	HHFXD63B175	CFD63B175	FD63B175	HFD63B175	HHFD63B175	FD63T175
200	3	FXD63B200	HFXD63B200	HHFXD63B200	CFD63B200	FD63B200	HFD63B200	HHFD63B200	FD63T200
225	3	FXD63B225	HFXD63B225	HHFXD63B225	CFD63B225	FD63B225	HFD63B225	HHFD63B225	FD63T225
250	3	FXD63B250	HFXD63B250	HHFXD63B250	CFD63B250	FD63B250	HFD63B250	HHFD63B250	FD63T250

Frames - Magnetic Trip Only - ETI Motor Circuit Protector

Ampere Rating	Poles	Minimum	Maximum	FXD6	CFD6
150	3	400	800	FXD63L150	CFD63L150
150	3	800	1500	FXD63A150	CFD63A150
150	3	1100	2500	FXD63H150	CFD63H150
250	3	1100	2500	FXD63A250	CFD63A250

Frames - Molded Case Switch - Circuit Disconnect

Ampere Rating	Poles	FXD6	HFXD6	CFD6
250	2	FXD62S250A	HFXD62S250A	—
250	3	FXD63S250A	HFXD63S250A	CFD63S250A

Terminals / Wire Ranges (Lug Information)

Lugs For 75°C Wire	
Catalog Number	Wire Range
TA1FD350A	#6—350 kcmil Cu #4—350 kcmil Al
TC1FD350	#6—350 kcmil Cu
Compression Lug	
CCF250	350 kcmil Cu/Al

Shunt Trip Combinations

Control Voltage		1 Shunt Trip
AC	DC	Catalog Number
24	—	S17FD60
120	—	S01FD60
240	—	S03FD60
277	—	S15FD60
480	—	S04FD60
600	—	S06FD60
—	12	S16FD60
—	24	S07FD60
—	48	S09FD60
—	125	S11FD60
—	250	S13FD60

Auxiliary Switch Combinations / Alarm Switch Combinations

Maximum Voltage		Combinations	Catalog Number
AC	DC		
240	—	1 Auxillary Switch	A01FD62
240	—	2 Auxillary Switches	A02FD62
480	—	1 Auxillary Switch	A01FD64
480	—	2 Auxillary Switches	A02FD64
—	12	2 Aux Switches- Gold Plated Contacts - For PLC Use	A01FDLV
480	250	1 Alarm Switch	B00FD64
480	250	1 Alarm Switch & 1 Auxillary Switch	C01FD64

Undervoltage Trip Combinations

Control Voltage		1 Undervoltage Trip	1 Undervoltage Trip and 1 Auxillary Switch
AC	DC	Catalog Number	Catalog Number
120	—	U01FD60	W01FD64
208	—	U02FD60	W02FD64
240	—	U03FD60	W03FD64
277	—	U16FD60	W16FD64
480	—	U06FD60	W06FD64
600	—	U08FD60	—
—	24	U13FD60	W13FD64
—	48	U14FD60	W14FD64
—	125	U10FD60	W10FD64
—	250	U12FD60	W12FD64

Siemens Industry, Inc.
5400 Triangle Parkway
Norcross, GA 30092

1-800-241-4453
info.us@siemens.com

Subject to change without prior notice
Order No. CBDS-FDGEN-0717
Printed in USA
All Rights Reserved
© 2017, Siemens Industry, Inc.
usa.siemens.com/circuitbreakers

The technical data presented in this document is based on an actual case or on as-designed parameters, and therefore should not be relied upon for any specific application and does not constitute a performance guarantee for any projects. Actual results are dependent on variable conditions. Accordingly, Siemens does not make representations, warranties, or assurances as to the accuracy, currency or completeness of the content contained herein. If requested, we will provide specific technical data or specifications with respect to any customer's particular applications. Our company is constantly involved in engineering and development. For that reason, we reserve the right to modify, at any time, the technology and product specifications contained herein.