



**Note:**  
 - Drawings Not To Scale  
 - Drawings Subject to Change Without Notice  
 - Dimensions are inches next to [Millimeters]

Part No.:  
**T36BN13G7**

**Schneider Electric**  
 Schneider Electric United States  
 North American Division  
 Boston One Campus  
 800 Federal Street  
 Andover, MA 01810, USA  
 Phone: +1 8773425173  
 Email: CCC@us.schneider-electric.com

**Technical Information:**

Max. Continuous Current Rating:	600V / 18A
Certifications:	UL Listed, CSA, CE
RoHS:	Yes
Termination Method:	Power Line: Screw Clamp, Power Load: Lug, Control Circuit: Screw Clamp
Weight (lbs):	5.92
Power Line Size (AWG):	#8 - #18
Power Load Size (AWG):	#4 - #14
Control Wire Size (AWG):	#10 - #18
Thermal Overload Type:	Motor Logic Solid State
Thermal Overload Trip Class:	Class 10/20 Selectable
Mounting:	Panel

**Specification:**

Description	TeSys N Sz 0 open starter, 3 pole, 120 VAC					
Type	FVNR					
Voltages Code:	G7 at 120VAC					
Control Type:	Common control					
Coil Consumption:	Inrush 70 VA Sealed 7 VA					
	Single Phase			Three Phase		
	115V	230V	200V	230V	460V	575V
	1 HP	2 HP	3 HP	3 HP	5 HP	5 HP